

SWAP

Safewash P

DESCRIPTION

SWAP removes all types of flux residues (RA, RMA, no-clean and water-soluble) quickly and efficiently, using a range of different production equipment. It is designed as a ready to use version of SWAF and also contains a corrosion inhibitor for use with sensitive metals. SWAP is part of the Safewash range; water-based, non-flammable, biodegradable solvent blends designed to clean to within military cleanliness standards, (ANSI-J-001B/IPC TM-650).

READ ENTIRE TECHNICAL BULLETIN BEFORE USING THIS PRODUCT

FEATURES AND BENEFITS

- Removes all types of flux residues; suitable for many PCB cleaning processes
- Low foaming action; suitable for use in pressure wash systems
- Supplied as ready-to-use product, quick and easy processing
- Non-flammable product, 100% ozone friendly; suitable for use in standard cleaning equipment

APPROVALS

Standard	Status
RoHS Compliant (2015/863/EU)	Yes

PRODUCT INFORMATION

For available packaging sizes please visit:

electrolube.com

PHYSICAL PROPERTIES

Category	Results
Typical Properties Concentrate	
Appearance	Blue Liquid
Density @ 20 °C (g/mL)	1.00
pH	11.7
Boiling Point (°C)	98
Flash Point (°C)	None
Freezing Point (°C)	-5
Viscosity @ 20 °C (mPa s)	25 to 30
Conductivity @ 18 °C (mS)	1.0

APPLICATION GUIDELINES

SWAP has been specifically developed for use in 3 or 4 stage batch cleaning systems using ultrasonic or spray-under-immersion. It is supplied at a concentration suitable for immediate use and further dilution is not recommended. In typical usage times and temperatures, SWAP has excellent compatibility with most materials used in the electronics industry, and with materials used in cleaning equipment. For sensitive plastics such as polycarbonate and ABS, testing is recommended to confirm compatibility.

Stage 1 – Cleaning

Typically, 3 to 5 minutes with agitation. Safewash is designed to be used at ambient temperature, though if required this can be increased up to 45 °C.

Stage 2 – Tap Water Rinse

The temperature of the rinsing solution can be ambient, but higher temperatures in addition to agitation, will accelerate and improve rinsing.

Stage 3 – Deionized Water Rinse

This may either consist of a re-circulating rinse or a spray system that is activated when the PCBs leave the tap water rinse. If military standard cleanliness is not required, this deionized rinse may not be necessary, though the PCBs may show some white streaking due to tap water impurities.

For ferrous metal cleaning operations, it is possible to add a rust inhibitor (Code: SRIA) at 0.5% into this stage. This will prevent flash rusting of ferrous metals when they are dried at high temperatures.

Stage 4 – Drying

The length of time required to dry the PCB depends on the circuit design and the efficiency of the drying unit itself. This is enhanced by equipment that uses high air flow as opposed to 'heat only' systems. In general, this stage takes approximately 5 minutes at 90 °C. Air-knives can be used as an optional extra to reduce temperature or total energy required.

Evaluation of Flux Concentration - Conductivity Method

The electrical conductivity of a Safewash solution will increase with flux concentration (and other ionic contaminants). Once it has been determined how much flux the Safewash can take up, while still achieving the cleanliness level required, the method below can be used to determine a method for monitoring the solution.

Whilst conductivity and other methods may be used to assess the contamination level, the critical test for replacement is when the process is not cleaning the boards to the desired standards.

A range of flux / Safewash solutions should be made up at 0.5, 2.5, 5, 7.5, 10 and 15%.

For solder pastes, thoroughly mix 100g of the paste with 100g of Safewash. Heat the mixtures to 50 °C for 4 hours. Cool to room temperature and measure the conductivity of the liquid at a suitable fixed temperature. If the flux content of the paste is 10%, this gives a figure for the 10% flux in Safewash. Serial dilution of this master solution will allow a graph of conductivity/ concentration to be prepared.

For wave solder fluxes, take 150mL of a 10% flux and evaporate to ca. 50mL. (CARE - solvent is usually highly flammable). Dissolve this material in 100mL of Safewash to give a standard 15% solution. Measure conductivity at 20°C and construct a graph. In production, the conductivity of the cleaning solution may now be monitored. When the conductivity indicates flux levels of 10 to 15%, or a concentration above which Safewash does not clean to an acceptable level, the bulk material should be replaced.

As an alternative, pH, refractive index or titration are also suitable methods for monitoring the contamination level in Safewash.

Estimated SWAP Usage

Usage will depend greatly on PCB design; however, it can be estimated from the concentration of flux used and the size/number of boards cleaned. The table below lists the typical amount of contamination expected on a PCB.

Flux Concentration	Contamination per square meter of PCB
20%	11 to 13 grams
10%	5 to 8 grams
5%	2 to 5 grams

SWAP will absorb a maximum of 5 to 15% of its weight of flux while still cleaning to military standards.

In addition to the SWAP that it is used to absorb the flux, small amounts of cleaner will remain on the board and be transferred into the rinse stage. This is commonly known as drag-out, which typically results in loss of around 100mL/m² of board cleaned.

ADDITIONAL INFORMATION

Safewash has been tested and approved by both military and commercial electronics manufacturing companies across the world. The British Ministry of Defense (Directorate General of Defence Quality Assurance) have tested Safewash on various fluxes and have found that the product cleans to well within Defence Standard 00-10 (and it performed approximately 10 times better than 1.1.1. Trichloroethane based solvents).

Siemens Central Research Laboratories in Erlangen agreed with these findings. Their conclusions were:

"The residual contamination found on the circuit boards and components after cleaning with Safewash 2000 is significantly below the limit value of 1.56 micrograms NaCl/cm² permitted by MIL-P28809A. From the point of view of a high level of cleaning efficiency, the bio-cleansing agent "Safewash 2000" can be released for cleaning purposes in electrical engineering".

Disposal

The contamination levels after a single use are normally low enough to allow the solution to run directly to the drain or recycled through a carbon filter; this will prevent the rinse water becoming progressively more contaminated. The local water authority should be consulted for confirmation of this. Similarly, the rinse water can usually be run to the drain. Experience shows that a flow rate of approx. 20 liters per square meter of PCB cleaned produces water with acceptable levels of contamination. The use of a carbon filter, through which the tap water is permanently re-circulated, produces no liquid waste.

Shelf Life: 48 Months

SAFETY & WARNING

It is recommended that the company/operator read and review the Safety Data Sheets for the appropriate health and safety warnings before use. **Safety Data Sheets are available.**

CONTACT INFORMATION

To confirm this document is the most recent version, please contact

TechnicalSupportTeam@hkw.co.uk

www.electrolube.com

North America 109 Corporate Blvd. South Plainfield, NJ 07080, USA 1.800.367.5460	Europe Ashby Park Coalfield Way Ashby de la Zouch Leicestershire, LE65 1JR, UK 44.01530.41960	Asia 8/F., Paul Y. Centre 51 Hung To Road Kwun Tong, Kowloon, Hong Kong 852.3190.3100
--	---	--

Also read carefully warning and safety information on the Safety Data Sheet. This data sheet contains technical information required for safe and economical operation of this product. READ IT THOROUGHLY PRIOR TO PRODUCT USE. Emergency safety directory assistance: US 1 202 464 2554, Europe + 44 1235 239 670, Asia + 65 3158 1074, Brazil 0800 707 7022 and 0800 172 020, Mexico 01800 002 1400 and (55) 5559 1588

DISCLAIMER: All statements, technical information and recommendations contained herein are based on tests we believe to be reliable, but the accuracy or completeness thereof is not guaranteed. No statement or recommendation shall constitute a representation unless set forth in an agreement signed by officers of seller and manufacturer. NO WARRANTY OF MERCHANTABILITY, WARRANTY OF FITNESS FOR A PARTICULAR PURPOSE OR ANY IMPLIED WARRANTY IS MADE. The following warranty is made in lieu of such warranties and all other warranties, express, implied, or statutory. Products are warranted to be free from defects in material and workmanship at the time sold. The sole obligation of seller and manufacturer under this warranty shall be to replace any noncompliant product at the time sold. Under no circumstances shall manufacturer or seller be liable for any loss, damage or expense, direct, indirect, incidental or consequential, arising out of the inability to use the product. Notwithstanding the foregoing, if products are supplied in response to a customer request that specifies operating parameters beyond those stated above, or if products are used under conditions exceeding said parameters, the customer by acceptance or use thereof assumes all risk of product failure and of all direct, indirect, incidental and consequential damages that may result from use of the products under such conditions, and agrees to exonerate, indemnify, defend and hold harmless MacDermid, Incorporated and its affiliates therefrom. No suggestion for product use nor anything contained herein shall be construed as a recommendation to use any product in a manner that infringes any patent or other intellectual property rights, and seller and manufacturer assume no responsibility or liability for any such infringement.

© 2019 MacDermid, Inc. and its group of companies. All rights reserved. "(R)" and "TM" are registered trademarks or trademarks of MacDermid, Inc. and its group of companies in the United States and/or other countries.